# 80A Mini AC/DC Clamp Meter

### *Small diameter elongated jaw*

*Designed for high resolution current measurements in hard to reach locations. This mini-clamp performs AC and DC low current tests where typical clamps cannot go.*




## Features:

- 4000 count LCD display
- 4A range with 1mA resolution for accurate low current measurements
- Jaw opens to 0.5" (12.7mm)
- AC/DC Voltage, Resistance, Frequency, Capacitance, and Duty Cycle
- Diode Test/Continuity Beeper
- Data Hold
- Complete with test leads, two 1.5V AAA batteries, and carrying case



Mini size jaw conveniently reaches into narrow spaces for taking Current measurements where typical clamp size meters cannot go.

| Specifications | Range | Resolution | Accuracy (%rdg+digits) |
|---|---|---|---|
| AC Current | 4A, 80A | 1mA | ±(2.5% + 5d) |
| DC Current | 4A, 80A | 1mA | ±(2.5% + 4d) |
| AC Voltage | 400mV to 600V | 0.1mV | ±(2.0% + 4d) |
| DC Voltage | 400mV to 600V | 0.1mV | ±(1.5% + 3d) |
| Resistance | 400Ω to 40MΩ | 0.1Ω | ±(1.5% + 2d) |
| Frequency | 5Hz to 10MHz | 0.001Hz | ±(1.2% + 3d) |
| Duty Cycle | 5 to 99.9% | 0.1% | ±(1.2% + 3d) |
| Dimension/Weight | 8.3x2.8x1.5" (210x70x37mm)/7oz (200g) | | |

## Ordering Information:

**380950** .....80A Mini AC/DC Clamp Meter

CE EN 61010-1 CAT III 600V



*Specifications subject to change without notice.*
*Copyright © 2007-2011 Extech Instruments Corporation. All rights reserved including the right of reproduction in whole or in part in any form.*